



• Front-Panel Port



• Expansion Module



NOTE: The slide-in modules are hot-swappable, you do not need to power off the switch before installing or removing a module.



- Direct Attach Cable (DAC)
- SFP+ transceivers

front 10G ports



Console#switch stacking-port option ?

<1-2> the option of stacking port

(option 1 is front 10G ports such as port 25-26 in GTL-2881)

Console#switch stacking-port option 1 ?

<1-8> unit number

Console#switch stacking-port option 1 1

After setting, please reload the switch.

You can check the setting by using "show stacking-port option" command.

```

Console#show switch stacking-port option
Stacking-port Option status:
Switch ID  Config Option  Active Option
-----
1          1          1

```

rear 10G ports (Add purchase MDU-0211 module)



Console#switch stacking-port option ?

<1-2> the option of stacking port

(option 2 is rear 10G ports such as port 27-28 in GTL-2881)

Console#switch stacking-port option 2 ?

<1-8> unit number

Console#switch stacking-port option 2 1

After setting, please reload the switch.

You can check the setting by using "show switch stacking-port option" command.

```
Console#show switch stacking-port option
Stacking-port Option status:
Switch ID  Config Option  Active Option
-----
1          2          2
```